



马力 HP	极数 (KW)	输出功率 (KW)	三相										转数		单相			
			200	208	220	230	240	346	380	415	460	480	50Hz	60Hz	110	220	240	
1/4	2P	0.19	1.2	1.2	1.1	1.1	1	0.7	0.6	0.6	0.5	0.5	2785	3385	4.6	2.3	2.1	
1/2		0.37	2.4	2.4	2.2	2.2	2.1	1.4	1.3	1.2	1.2	1	2785	3350	8.0	4.0	3.7	
1		0.75	4.2	4	3.8	3.8	3.6	2.4	2.2	2	1.9	1.8	2810	3355	13	6.5	6	
2		1.5	7.3	7	6.5	6.4	6.2	4.2	3.8	3.5	3.2	3.3	2820	3400	18	9	8	
3		2.2	10	9.8	9.0	8.7	8.3	5.8	5	4.9	4.4	4.2	2840	3410	40	20	44	
5		3.7	16	15.5	14.5	14.0	13.5	9.4	8.6	7.8	7	6.6	2850	3450	-	-	-	
1/4	4P	0.19	1.8	1.6	1.6	1.5	1.4	1.1	0.9	0.8	0.75	0.7	1400	1650	4	2	2.8	
1/2		0.37	2.8	2.6	2.5	2.3	2.1	1.6	1.4	1.3	1.1	1	1410	1695	9.4	4.7	4.2	
1		0.75	4.5	4.4	4	3.7	3.3	2.6	2.3	2.2	1.9	1.8	1420	1710	16	8	7.2	
2		1.5	7.7	7.4	7	6.7	6.5	4.6	4	3.7	3.4	3.3	1420	1715	28	14	13	
3		2.25	10.6	10.2	9.6	9.2	8.8	6	5.5	5.1	4.6	4.4	1430	1735	42	21	19	
5		3.75	16	15.4	15	14.5	14	9.3	8.6	7.7	7.2	7	1430	1730	72	36	32.5	
7.5		5.6	25	24	23	22.3	21	14.6	13	12	11	10.8	1440	1740	-	-	-	
10		7.5	34	33	31	3	29	19.5	18	16.4	15.1	14.5	1440	1740	-	-	-	
15		11	48.5	46	44	42.5	41	28	25	23	21.3	20.5	1440	1750	-	-	-	
20		15	64	61.5	58	56	54.5	37	33.5	30.7	28	27.3	1440	1750	-	-	-	
25		18.7	78	76	71	68.5	67	45	41	38	34.3	33.5	1440	1750	-	-	-	
30		22.5	92	88	83	80	77	52.8	48	44	40	38.5	1440	1760	-	-	-	
40		30	124	116	112	108	105	71	64.5	58	54	52.5	1440	1760	-	-	-	
1/4		6P	0.19	2	1.9	1.8	1.8	1.7	1.15	1	0.95	0.9	0.8	930	1120	9	4.5	4.3
1/2	0.37		3.2	3	2.9	2.8	2.7	1.8	1.7	1.5	1.4	1.3	930	1135	12	6	5.5	
1	0.75		5	4.8	4.6	4.5	4.3	2.9	2.7	2.4	2.2	2.1	930	1140	20	10	9	
2	1.5		8.5	8.2	7.7	7.4	7.1	4.9	4.5	4.1	3.7	3.5	940	1140	30	15	14	
3	2.25		11.5	11.2	10.6	10.2	9.8	6.7	6	5.6	5.1	5	940	1160	50	25	23	
5	3.75		18.7	18	17	16.4	16	10.8	9.8	9	8.2	8	940	1160	-	-	-	
7.5	5.6		27.8	26	25	24.1	23.4	16	14.5	13	12.1	11.7	940	1160	-	-	-	
10	7.5		36.5	35	33	31.8	30.7	21	19	17.5	16	15.4	940	1165	-	-	-	
15	11		52	50	47	46	44	30.5	27	25	23	22	940	1165	-	-	-	
20	15		70	67	63	60	58	39	35.5	32	30	29	940	1170	-	-	-	
25	18.7		81	77.2	73	70	67	47.5	43.4	40	35	33	950	1170	-	-	-	
30	22.5		106	102	97	95	89	61	55	51	46	44.2	950	1170	-	-	-	
1/4	8P		0.2	3.3	3.2	3	2.8	1.9	1.7	1.6	1.4	1.4	1.4	710	1120	-	-	-
1/2			0.37	5	4.8	4.5	4.2	4.1	2.9	2.6	2.4	2.2	2.1	710	1135	-	-	-
1		0.75	6	5.3	5	4.8	4.6	3.2	2.9	2.7	2.4	2.3	720	1140	-	-	-	
2		1.5	8.8	8.5	8	7.7	7.3	5.1	4.6	4.2	3.8	3.7	720	1135	-	-	-	

注：此表为50HZ测试值，60HZ使用时电流降低5%。

未标注电流表示无该马力产品，其他特殊电压未标示请咨询本公司品管部。